

POWER EXTENSION SOCKET**NEW****MINI USB CHARGER****P/No. A13-234****Features:**

- Rating : Input : 12~24V DC. USB output : 5V 2.4A / 1A max
- **A13-234A** : LED illuminated frame
- **A13-234B** : black frame
- **A13-234C** : laser-engraving legend frame
- Snap in USB charger
- Reversed polarity protection
- **A13-234AUW-W1** : 5V 2.4A max, blue LED illuminated frame, 2.5A glass tube fuse max
- **A13-234B-W1** : 5V 1A max, black, without LED, 1.5A glass tube fuse max
- **A13-234CUB-W1** : 5V 2.4A max, laser-engraving legend frame, 2.5A glass tube fuse max
- **A13-234CUB-W2** : 5V 1A max, laser-engraving legend frame, 1.5A glass tube fuse max
- **A13-234CUB-W3** : 5V 2.4A max, laser-engraving legend frame, without fuse
- Assemble the power convert and fuse #R3-48 with 0.185"SQ terminal
- Optional accessories : Holder #PR18-B5
- Mounting hole : \varnothing 20.2 mm
- Size: 22.9 (D) x 24.8 (H) mm (wire harness not included)

**A13-234AUW-W1****DUAL USB CHARGER****P/No. A13-230****Features:**

- Rating : Input : 12~24V DC. USB output : 5V 2.1A+2.1A max., 2 ports
- Screw in USB charger with dust-proof cover
- Reversed polarity protection
- Backlighting power indication shown per laser-engraving legend on panel
- Customized legends on the dust-proof cover and on the laser-engraving panel are available
- Optional accessories : single / dual / triple mounting panel and surface mount case
- Mounting hole : \varnothing 29.0 mm
- Size : 36.8 (D) x 50.4 (H) mm

**DUAL USB CHARGER****P/No. A13-236****Features:**

- Rating : Input : 12~24V DC. USB output : 5V 2.1A + 2.1A max., 2 ports
- Snap in USB charger with dust-proof cover
- **A13-236AU-BB3** : 0.250" quick terminals
- **A13-263BU-BB3** : 22AWG wire
- Reversed polarity protection
- Backlighting power indication shown per laser-engraving legend on panel
- Customized legends on the dust-proof cover and the laser-engraving panel are available
- Optional accessories: Panel #PR18-E2/3/4-B
- Mounting hole : 36.6 (W) x 21.2 (H) mm
- Size : 49.0 (L) x 24.2 (W) x 49.1 (H) mm



*All the specifications are subject to change without notice.



Headquarters:
TEL : 886-6-2532181
FAX : 886-6-2532633

Taipei Branch Office:
TEL : 886-2-25014062-4
FAX : 886-2-25040685

China Factory:
TEL : 86-752-3897988
FAX : 86-752-3897986
www.shinchin-sci.com

Hong Kong Branch:
TEL : 852-27939773
FAX : 852-27939830

Indonesia Factory:
TEL : 62-24-7627048
FAX : 62-24-7627047